

# MITSUBISHI MGS SERIES

DIESEL GENERATOR SET  
60Hz/1800 rpm/6.6kV/13.8kV



## MGS1500HV

60Hz/6.6kV/13.8kV

POWER RATING (0.8 P.F.)		MODEL CODE
PRIME	1460 kW	66CP-P620 61CP-P623
CONTINUOUS	1240 kW	66C-P620 61C-P623



MGS1500HV with typical options

### CONDITIONS & DEFINITIONS

#### Prime [PRP] : Code:CP

Applicable for supplying power with varying load instead of the utility for an unlimited time. +10% overload is allowed in accordance with ISO3046/1. Prime power in accordance with ISO15550, ISO3046/1, JIS8002-1, DIN6271 and BS5514. Prime power in accordance with ISO8528.

#### Continuous: Code:C

Applicable for supplying power continuously. Continuous power in accordance with ISO8528, ISO15550, ISO3046/1 and BS5514.

#### Conditions:

Engine ratings are based on SAE J1349 standard conditions and also apply at ISO3046/1, DIN6271 & BS5514 standard conditions.

Fuel rates: based on ASTM D975, BS2869 and on fuel oil of 35° API (16°C or 60° F) gravity having a LHV of 42,780 kJ/kg (18,390 Btu/lb.) when used at 29°C (85° F) and weighing 838.9 g/liter (7.001 lbs./U.S. gal.).

Note: \* Please consult with your nearest Mitsubishi MGS dealer for additional rating requirements.

### DIMENSION (Reference Data)

			PRIME	CONTINUOUS
			1460 kW	1240 kW
Overall dimensions	L : Length	mm	5820	6300
	W : Width	mm	2160	2590
	H : Height	mm	2935	3085/3105
Total Weight (Dry)	(P620/P623)	kg	15300/15600	15900/16200
Total Weight (Wet)	(P620/P623)	kg	15970/16270	16660/16960

# MITSUBISHI MGS SERIES

DIESEL GENERATOR SET  
MGS1500HV



## MGS SERIES DIESEL ENGINE: MITSUBISHI S16R-PTA-S(Prime) S16R-PTA-2(Continuous)

V-16, 4 stroke-cycle water-cooled, turbocharged and aftercooled

### ENGINE SPECIFICATIONS & TECHNICAL DATA

Bore	mm	170
Stroke	mm	180
Displacement	L	65.37
Piston speed	m/sec.	10.8
Compression ratio		14.0(*1)
Lubricating oil capacity	L	230(*2)
Coolant capacity without/with radiator	L	170/383(*3)
Coolant pump external resistance	m water	3.5
Coolant pump flow rate	L/min	1850
Cooling fan airflow rate	m <sup>3</sup> /min	2040
Cooling fan air flow restriction	kPa	0.1
Ambient air temperature	°C	40
Allowable exhaust back pressure	kPa	6.0
Exhaust flange size (internal diameter)	mm	350

(\*1) S16R-PTA-2:15.0 (\*2) S16R-PTA-2:290L (\*3) Continuous 170/398L

### ENGINE OPERATING DATA

		<b>PRIME</b> 1460 kW	<b>CONTINUOUS</b> 1240 kW
Gross Engine Power*	kWm	1540	1310
Brake mean effective pressure	MPa	1.6	1.4
Regenerative absorption	kW	192	192
Noise Level at 1 m (excluding: intake, exhaust & fan)	dB(A)	110	109
Fuel consumption load 100%*	L/hr.	384	339
Fuel consumption load 75%*	L/hr.	297	279
Combustion air inlet flow rate	m <sup>3</sup> /min	148	124
Exhaust gas flow rate	m <sup>3</sup> /min	392	329
Exhaust gas temperature	°C	510	500
Heat rejection to coolant	kW	1081	908
Heat rejection to exhaust	kW	1523	1256
Heat rejection to atmosphere from engine	kW	130	109
Heat rejection to atmosphere from generator	kW	93	79

\* WITH FAN basis.

Deration for engine

Note: Please consult with your nearest Mitsubishi MGS dealer

### ENGINE STANDARD EQUIPMENT

Aftercooler  
Turbocharger filter (For MGS-B, HV stand-by and prime)  
Paper element type filter (For MGS-C, HV PRP continuous)  
Structure steel base  
Crankcase breather  
Charging alternator  
Lubricating oil cooler  
Fuel filters, full flow paper element  
Fuel transfer pump, gear driven, plunger type  
Electronic type governor  
Jacket water heater \*  
Jacket water pump, gear driven  
Lubricating oil filter, full flow paper element  
Lubricating oil pump, gear driven  
Exhaust dry manifold  
Radiator, blower fan, fan drive  
Manual shutoff  
24V DC electric starting motor

\* Depending on the model, it becomes optional setting.

# MITSUBISHI MGS SERIES

DIESEL GENERATOR SET  
MGS1500HV



## MGS SERIES 7310 MK II GENERATOR CONTROL PANEL

### Features

MGS standard 7310 MK II programmable microprocessor generator control panel provides the following functions

- ◆ Start and stop control
- ◆ Engine and generator measurement items on LCD display and LED on the front panel for operation status indication
- ◆ Engine and generator shutdown and warning protection
- ◆ Generator breaker control
- ◆ Expansion module for additional output and input
- ◆ RS485 and RS232C communication for remote monitoring

### Mounting

Fabricated cubicle mounted on individual bracket with anti-vibration isolator

### Instrument and control accessories

- Generator running indicator
- Manual button
- Auto button
- CB open button (Manual only)
- CB close button (Manual only)
- Manual start button
- Manual Stop/Reset button
- Selector switch (ACTIVE, PANEL LOCK, STOP/RESET)
- Mute alarm button
- Menu navigation button
- Common alarm indicator
- Voltage adjuster
- Speed adjuster
- Emergency stop pushbutton

### Measured items on LCD display

- Generator volts L1-N, L2-N, L3-N
- Generator volts L1-L2, L2-L3, L3-L1
- Generator amps L1, L2, L3
- Generator Frequency Hz
- Engine speed RPM
- Engine oil pressure (PSI & Bar & kPa)
- Engine cooling water temperature (°C & °F)
- Battery volts
- Engine hours run
- Generator Load kW, kVA, kVar
- Generator Load kWh, kVAh, kVarh
- Power Factor
- Generator Phase Sequence

### Shutdown and Warning items on LCD display

- High coolant temperature : shutdown and warning
- Low oil pressure : shutdown and warning
- Fail to start : shutdown
- Over-speed : shutdown and warning
- Under-speed : shutdown and warning
- Loss of speed signal : shutdown
- Fail to stop : warning
- Over voltage (DC) : warning
- Under voltage (DC) : warning
- Lubrication oil filter clogged : warning
- High oil temperature : shutdown and warning \*1 \*2
- Oil pressure sender open circuit : shutdown
- Charge fail : warning
- Exhaust gas temperature high : warning \*1
- Coolant level low : warning \*1
- High crankcase internal pressure : shutdown \*1
- Generator high current : shutdown (IDMT) and warning
- Over voltage (AC) : shutdown and warning
- Under voltage (AC) : shutdown and warning
- Over frequency : warning
- Under frequency : warning
- Overload : warning
- Winding temperature high (U, V, W) : warning \*1
- Bearing temperature high : warning \*1
- Electrical trip
- Emergency stop : shutdown

\*1 : MGS-C, HV continuous are applicable as standard. The others are applicable as option.

\*2 : MGS2700 and MGS2800 are applicable as standard. The others are applicable as option.

### Operation status indicated by LED

- Remote start present
- Generator ready
- Lubrication oil filter clogged
- Electrical trip

# MITSUBISHI MGS SERIES

DIESEL GENERATOR SET  
MGS1500HV



## MGS SERIES AC GENERATOR MODEL: MG-KP620/623(PRIME) MG-KP620/623(CONTINUOUS)

### Features

MGS original design, single bearing(\*1), 4 pole, screen protected, self excited, self regulating and brushless with fully connected damper windings, salient pole rotors, A.C. exciter and rotating rectifier unit. Direct coupled to engine and regreaseable bearing, direct drive centrifugal blower.

With space heater.

Enclosure: Drip-proof IP23

Terminal box: Totally enclosed IP44

(\*1) KP623: double bearings

### Winding System

Standard 6 wire winding provides 3 phase voltage. All windings are impregnated in vacuum pressure impregnated with a special polyester resin.

Overspeed capability: 125% for 2 minutes

Insulation: Class 'H'

Temperature rise: 105°C(Prime),80°C(Continuous)

### Voltage Regulator

Fully sealed, 3 phase RMS sensing AVR with built-in protection against sustained over-excitation.

Voltage regulation: Less than +/- 0.5% from no load to full load at any power factor between 0.8 lagging and 1.0 allowing for a 4% engine speed variation

Voltage adjustment: +/- 6%

Wave form: Less than 5% deviation

### Permanent Magnet Generator (PMG)

Separately excited system which provide isolated power supply for the AVR – sustain short circuit current approximately 250-300% under fault condition.

### Sensors

Temperature sensors are provided as follows.

Stator winding, 2 per each phase, PT100

Bearing, PT100(\*2) (\*2) KP623: 1 per each bearing

\*Generator winding and bearing temperature indication Meters are option.

### Electrical Design

In accordance with ISO 8528-3, IEC60034-1/BS EN60034-1, BS5000 Part 3, VDE0530, NEMA MG1-32, CSA22-2-100 and AS1359.

Telephone Influence Factor (TIF): Less than 50

## Gen Set Option Features

### ■ ENGINE

Air Cleaner, paper element dry type  
(For MGS-B, HV stand-by and prime only)

Battery Kit

Battery Charger

Anchor Bolts

### ■ FUEL

Fuel Day Service Tank

### ■ COOLING

Oversize radiator

Heat Exchanger

Expansion Tank

Removal STD Radiator, Fan & Fan Drive

### ■ LUBRICATION

Lub. Oil Level Regulator

### ■ EXHAUST

Exhaust Silencer

Exhaust Flexible Pipe

### ■ GENERATOR

Power Factor Regulator

### ■ CONTROL PANEL

Diesel Generator Integrated Communication Synthesizer  
(DGICS-MII)

Auxiliary Control Panel

Remote Monitor Interface

2157 expansion unit (Output signal module)

2130 expansion unit (Input signal module)

2133 expansion unit (RTD/Thermocouple input module)

### ■ SWITCHGEAR

Circuit Breaker MCCB & ACB

Reverse Power Relay



**MITSUBISHI HEAVY INDUSTRIES  
ENGINE SYSTEM ASIA**

No. 3, Tuas Avenue 12, Singapore 639024

Republic of Singapore

Phone:65-6862 2202 Fax: 65-6862 5728

URL: <http://www.mhiesa.com/>

COMPANY WITH  
QUALITY SYSTEM  
CERTIFIED BY DNV GL  
= ISO 9001:2015 =

Mitsubishi Heavy Industries Engine System Asia Pte Ltd, serves for the customers with improved products continually.  
Therefore specification and some materials will be changed without notice.  
The International System of units (SI) is used in this publication.